

How to Restore Factory Defaults of your GalaxyHDX and HDX2

Following this procedure will allow you to restore the Factory Default NVRAM to a GalaxyHDX or HDX2 controller. While this will not affect the data stored on any valid RAID sets or the RAID set configuration, it does remove any Host-LUN Mapping and Static IP Address settings. These settings will need to be reapplied after this procedure. To begin, the RAID must be powered off.

LCD Panel Display	Instructions
	With <ENT> and <ESC> held down, power on the chassis
Maintenance Mode	Press <ENT>
FW Download	Press down arrow once
Restore Factory Defaults	Press and hold <ENT>
Factory Defaults Restored!	Press down arrow three (3) times
Reset Controller	Press and hold <ENT>
Resetting...	Factory Defaults have been restored. Chassis booting normally